



### Introduction

The I-7050 series of modules offers channels for digital input and 8 channels for digital output, each of which are non-isolated. The I-7050 supports sink-type output using an NPN open collector, and source-type input. All input channels are able to be used as 16-bit counters. There are also options to enable both power-on and safe values. The I-7050D has 15 LED indicators that can be used to monitor channel status. The M-7050 has the same hardware specifications as the I-7050 , but provides additional support for the Modbus RTU protocol

#### System Specifications

| Model                                     | I-7050   | I-7050D   | I-7050A       | I-7050AD  |
|---|--|---|---------------|---|
|   | M-7050   | M-7050D   |               |   |
| Communication                             |  |   |               |   |
| Interface                                 | RS-485   |   |               |   |
| Bias Resistor                             | No (Usually supplied by the RS-485 Master. Alternatively, add a tM-SG4 or SG-785.) |   |               |   |
| Format                                    | (N, 8, 1) (N, 8, 2) (E, 8, 1) (O, 8, 1)  |   |               |   |
| Baud Rate                                 | 1200 to 115200 bps   |   |               |   |
| Protocol                                  | DCON (For I-7050 series)   |   |               |   |
| FIOLOCOI                                  | Modbus RTU,  | DCON (For M-7   | '050 series)  |   |
| Dual Watchdog                             | Yes, Module (1.6 Seconds), Communication (Programmable)                            |   |               |   |
| LED Indicators/Display                    |  |   |               |   |
| System LED Indicator                      | Yes, 1 as Pow  | er/Communicat   | ion Indicator |   |
| I/O LED Indicators                        | -  | Yes, 7 LEDs<br>as Digital<br>Input and<br>8 LEDs as<br>Digital Output<br>Indicators | -             | Yes, 7 LEDs<br>as Digital<br>Input and 8<br>LEDs as Digi-<br>tal Output<br>Indicators |
| 7-segment LED Display                     | -  |   |               |   |
| Isolation                                 |  |   |               |   |
| Intra-module Isolation,<br>Field-to-Logic | -  |   |               |   |
| EMS Protection                            |  |   |               |   |
| ESD (IEC 61000-4-2)                       | -  |   |               |   |
| EFT (IEC 61000-4-4)                       | -  |   |               |   |
| Surge (IEC 61000-4-5)                     | -  |   |               |   |
| Power                                     |  |   |               |   |
| Reverse Polarity Protection               | Yes  |   |               |   |
| Input Range                               | +10 ~ +30 V <sub>DC</sub>  |   |               |   |
|   | 0.4 W  | 1.1 W   | 0.5 W         | 1.2 W   |
| Consumption                               | 0.4 W  | 1.1 W   |               | 1   |
| Mechanical                                |  |   |               |   |
| Dimensions (L x W x H)                    | 123 mm x 72 mm x 35 mm   |   |               |   |
| Installation                              | DIN-Rail or Wall Mounting  |   |               |   |
| Environment                               |  |   |               |   |
| Operating Temperature                     | -25 to +75°C   |   |               |   |
| Storage Temperature                       | -40 to +85°C   |   |               |   |
| Humidity                                  | 10 to 95% RH, Non-condensing   |   |               |   |

as well as the DCON protocol.


### Applications

Building Automation, Factory Automation, Machine Automation, Remote Maintenance, Remote Diagnosis, Testing Equipment.


### I/O Specifications


| Model             |  | I-7050                      | I-7050D        | I-7050A     | I-7050AD |  |
|-------------------|--|-----------------------------|----------------|-------------|----------|--|
|                   |  | M-7050                      | M-7050D        |             |          |  |
| Digital Ir        | Digital Input/Counter                    |                             |                |             |          |  |
| Channels          | Channels                                 |                             | 7              |             |          |  |
| Tuno              | Dry Contact                              | Sink                        |                |             |          |  |
| Туре              | Wet Contact                              | Source                      |                | Sink        |          |  |
| Wet<br>Contact    | ON Voltage Level                         | -                           |                | +4 ~ 30 VDC |          |  |
|                   | OFF Voltage Level                        | -                           |                | +1 VDC Max. |          |  |
|                   | ON Voltage Level                         | Open -                      |                |             |          |  |
| Dry<br>Contact    | OFF Voltage Level                        | Close to GND -              |                |             |          |  |
|                   | Effective<br>Distance for Dry<br>Contact | 500 m Max                   |                |             |          |  |
|                   | Max. Count                               | 65535 (16-bit)              |                |             |          |  |
| Counters          | Max. Input<br>Frequency                  | 100 Hz                      |                |             |          |  |
|                   | Min. Pulse Width                         | 5 ms                        |                |             |          |  |
| Input Imp         | Input Impedance                          |                             | 100 kΩ         |             |          |  |
| Channel-to        | Channel-to-Channel Isolation             |                             | -              |             |          |  |
| Overvoltag        | Overvoltage Protection                   |                             | -              |             |          |  |
| Digital O         | utput                                    |                             |                |             |          |  |
| Channels          | Channels                                 |                             | 8              |             |          |  |
| Туре              | Туре                                     |                             | Open Collector |             |          |  |
| Sink/Source       | Sink/Source (NPN/PNP)                    |                             | Sink Source    |             |          |  |
| Load Voltage      |  | +3.5 ~ 30 V <sub>DC</sub>   |                |             |          |  |
| Max. Load Current |  | 30 mA/Channel 50 mA/Channel |                | el          |          |  |
| Overvoltag        | Overvoltage Protection                   |                             | -              |             |          |  |
| Overload I        | Overload Protection                      |                             | -              |             |          |  |
| Power-on          | Power-on Value                           |                             | Yes            |             |          |  |
| Safe Value        | Safe Value                               |                             | Yes            |             |          |  |

## Internal I/O Structure




### Wire Connections






### Accessories

| tM-7520U CR | RS-232 to RS-485 Converter (RoHS)                     |
|-------------|---|
| tM-7561 CR  | USB to RS-485 Converter (RoHS)                        |
| tM-SG4 CR   | RS-485 Bias and Termination Resistor Module<br>(RoHS) |



## 🖿 Pin Assignments



# Ordering Information

| I-7050 CR     | 7-channel Non-isolated Digital Input and<br>8-channel Non-isolated Digital Output Module<br>using the DCON Protocol (Blue Cover) (RoHS)                   |  |
|---------------|---|--|
| I-7050-G CR   | 7-channel Non-isolated Digital Input and<br>8-channel Non-isolated Digital Output Module<br>using the DCON Protocol (Gray Cover) (RoHS)                   |  |
| I-7050D CR    | I-7050 with LED Display (Blue Cover) (RoHS)   |  |
| I-7050D-G CR  | I-7050 with LED Display (Gray Cover) (RoHS)   |  |
| I-7050A CR    | 7-channel Non-isolated Digital Input and<br>8-channel Non-isolated Digital Output Module<br>using the DCON Protocol<br>(Current Sink) (Blue Cover) (RoHS) |  |
| I-7050AD CR   | I-7050A with LED Display (Blue Cover) (RoHS)  |  |
| I-7050AD-G CR | I-7050A with LED Display (Gray Cover) (RoHS)  |  |
| M-7050-G CR   | 7-channel Non-isolated Digital Input and<br>8-channel Non-isolated Digital Output Module<br>using the DCON and Modbus Protocol (Gray<br>Cover) (RoHS)     |  |
| M-7050D-G CR  | M-7050 with LED Display (Gray Cover) (RoHS)   |  |

| I-7514U CR     | 4-channel RS-485 Hub (RoHS)  |
|----------------|--|
| SG-770 CR      | 7-channel Differential or 14-channel<br>Single-ended Surge Protector (RoHS)                                  |
| SG-3000 Series | Signal Conditioning Modules for Thermocouple,<br>RTD, DC Voltage, DC Current and Power Input<br>Transformers |